

SB BALLAST

CONTACTS

CONTACTS TYPE & QUANTITY				SERVICE RATING	CONTACTS TYPE & QUANTITY				SERVICE RATING
ARRANGEMENT	CONTACTS	SIZE	*		ARRANGEMENT	CONTACTS	SIZE	*	
	16S-1	7	16S	A		6	3 4	D	
	16-10	3	12	A		3	8	E	
	20-15	7	12	A		3	4	D	
	22-1	2	8	D		7	2 4 2 8 3 12	G = D Ball=A	
	22-2	3	8	D		9	3 4 6 16	A	
	22-22	4	8	A		2	0	D	
	24-11	9	3 8 6 12	A		8	4 4 4 16	D	
	24-2	7	12	D					
	28A-9	9	4 4 5 16	A					

* see Table C2

Male	Female	For type arrangement
Part N. SVKP16SMSs Size 16S	Part N. SVKP16SFSs Size 16S	16S-1
Part N. SVKP16SMS Size 16	Part N. SVKP16SFS Size 16	28A-9 28-22 32A-9 40A-10
Part N. SVKP12SMS Size 12	Part N. SVKP12SFS Size 12	16-10 20-15 24-11 24-2 28-10
Part N. SVKP08SMS Size 8	Part N. SVKP08SFS Size 8	22-1 22-2 24-11 28-3 28-10
Part N. SVKP04SMS Size 4	Part N. SVKP04SFS Size 4	28A-9 28-22 28-6 28-10 32A-9 40A-10
Part N. SVKP00SMS Size 0	Part N. SVKP00SFS Size 0	32-5



Size	Max Current	Rated Current	Max Voltage Drop	Wire section (mm ²)	Wire section AWG
0	245 A	150 A	53 mV	50÷60	0
4	135 A	80 A	58 mV	16÷20	4
8	73 A	46 A	65 mV	6÷8	8
12	41 A	23 A	63 mV	3	12
16	22 A	13 A	74 mV	1÷1,5	16
16S	22 A	13 A	74 mV	1÷1,5	16